


Current Transducer HAT 200 ... 1500-S/SP1

For the electronic measurement of currents: DC, AC, pulsed,..., with galvanic separation between the primary circuit and the secondary circuit.

$$I_{PN} = 200 \dots 1500 \text{ A}$$

$$U_{out} = \pm 4 \text{ V}$$



Electrical data

Type	Primary nominal RMS current	Primary current, measuring range ¹⁾	
	I_{PN} (A)	I_{PM} (A)	
HAT 200-S/SP1	200	±600	
HAT 400-S/SP1	400	±1200	
HAT 500-S/SP1	500	±1500	
HAT 600-S/SP1	600	±1800	
HAT 800-S/SP1	800	±2400	
HAT 1000-S/SP1	1000	±2500	
HAT 1200-S/SP1	1200	±2500	
HAT 1500-S/SP1	1500	±2500	
U_C	Supply voltage (±5 %) ¹⁾	±15	V
I_C	Current consumption	±20	mA
R_{INS}	Insulation resistance @ 500 V DC	> 1000	MΩ
U_{out}	Output voltage (Analog) @ ± I_{PN} , $R_L = 10 \text{ k}\Omega$, $T_A = 25 \text{ }^\circ\text{C}$	±4	V
R_{out}	Output internal resistance	100	Ω
R_L	Load resistance	> 10	kΩ

Accuracy - Dynamic performance data

ε	Error @ I_{PN} , $T_A = 25 \text{ }^\circ\text{C}$ (excluding offset)	≤ ±1	% of I_{PN}	
ε_L	Linearity error ²⁾ (0 ... ± I_{PN})	≤ ±1	% of I_{PN}	
U_{OE}	Electrical offset voltage @ $T_A = 25 \text{ }^\circ\text{C}$	< ±20	mV	
U_{OH}	Hysteresis offset voltage @ $I_p = 0$, after an excursion of $1 \times I_{PN}$	< ±10	mV	
TCU_{OE}	Temperature coefficient of U_{OE}	-40 °C ... +80 °C +80 °C ... +105 °C	< ±1 < ±1.5	mV/K mV/K
TCU_{out}	Temperature coefficient of U_{out} (% of reading)	< ±0.1	%/K	
t_{D90}	Delay time to 90 % of I_{PN}	< 5	μs	
BW	Frequency bandwidth ³⁾ (-3 dB)	DC ... 25	kHz	

General data

T_A	Ambient operating temperature	-40 ... +105	°C
T_S	Ambient storage temperature	-40 ... +105	°C
m	Mass	300	g
	Standards	EN 50178: 1997 UL 508: 2010 ⁴⁾	

Features

- Hall effect measuring principle
- Insulating plastic case recognized according to UL 94-V0.

Special feature

- Molex 5045-04AG.

Advantages

- Easy installation
- Low power consumption
- Small size and space saving
- Only one design for wide current ratings range
- High immunity to external interference.

Applications

- DC motor drives
- Switched Mode Power Supplies (SMPS)
- AC variable speed drives
- Uninterruptible Power Supplies (UPS)
- Battery supplied applications
- Power supplies for welding applications.

Application domain

- Industrial.

Notes: ¹⁾ Operating at $\pm 12 \text{ V} \leq U_C < \pm 15 \text{ V}$ will reduce the measuring range

²⁾ Linearity data exclude the electrical offset

³⁾ Please refer to derating curves in the technical file to avoid excessive core heating at high frequency

⁴⁾ UL conform is only applicable @ $T_A = -40 \text{ }^\circ\text{C} \dots +85 \text{ }^\circ\text{C}$.

N° 74.02.44.001.0, N° 74.02.48.001.0, N° 74.02.50.001.0, N° 74.02.52.001.0

N° 74.02.56.001.0, N° 74.02.60.001.0, N° 74.02.62.001.0, N° 74.02.65.001.0

10May2019/version 4

LEM reserves the right to carry out modifications on its transducers, in order to improve them, without prior notice

Current Transducer HAT 200 ... 1500-S/SP1

Insulation coordination

U_d	RMS voltage for AC insulation test, 50 Hz, 1 min	4.9	kV
U_{Ni}	Impulse withstand voltage 1.2/50 μ s	> 9.9	kV
		Min	
d_{CP}	Creepage distance	11	mm
d_{CI}	Clearance	11	mm
CTI	Comparative tracking index (group IIIa)	275	

Applications examples

According to EN 50178 and IEC 61010-1 standards and following conditions:

- Over voltage category III
- Pollution degree PD2
- Non-uniform field

	EN 50178	IEC 61010-1
d_{CP}, d_{CI}, U_{Ni}	Rated insulation voltage	Nominal voltage
Basic insulation	1100 V	1100 V
Reinforced insulation	550 V	550 V

Safety

This transducer must be used in limited-energy secondary circuits according to IEC 61010-1.



This transducer must be used in electric/electronic equipment with respect to applicable standards and safety requirements in accordance with the manufacturer's operating instructions.



Caution, risk of electrical shock

When operating the transducer, certain parts of the module can carry hazardous voltage (eg. primary busbar, power supply).

Ignoring this warning can lead to injury and/or cause serious damage.

This transducer is a build-in device, whose conducting parts must be inaccessible after installation.

A protective housing or additional shield could be used.

Main supply must be able to be disconnected.

