



Life Energy Motion

INTEGRATED CURRENT SENSOR SELECTION GUIDE



Precise, Compact, & Efficient Solutions

As the power density of electronic systems continues to rise, the demand for compact, efficient, and easy-to-integrate current sensing solutions is more critical than ever. Integrated Current Sensors (ICS) are designed to meet these evolving challenges by combining advanced sensing technology, signal processing, isolation, and system protection into a single, streamlined device. Leveraging decades of expertise in semiconductor design and packaging, LEM has developed a range of ICS that deliver highly accurate current measurements, ensuring optimal performance and safety in both current and future electronic designs.

From power supplies and battery management systems to e-motor drives and renewable energy networks, reliable current sensing is critical for maintaining efficiency, protection, and performance. However, shrinking PCB footprints and increasing power levels present challenges in thermal management, isolation, and EMI. ICS overcome these issues, offering a plug-and-play solution that integrates easily into space-constrained designs without compromising performance, embodying the principle of achieving more with less.

With LEM's range of ICS, engineers can confidently design high-performance electronics that support the growing demand for smarter, more energy-efficient solutions.



Integrated Current Sensor Portfolio

	Model	Measuring Range	Sensitivity	Nominal Current	Supply Voltage	Package	Bandwidth	Overcurrent Detection	Temperature Range	Output	AEC-Q Qualification	Visual Appearance
GO SME	GO 8-SME/SP4	20 A	62.5 mV/A	8 A	3.3 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Ratio	Grade 1	
	GO 10-SME	25 A	80 mV/A	10 A	5 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Fixed	Grade 1	
	GO 10-SME/SP3	25 A	50 mV/A	10 A	3.3 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Fixed	Grade 1	
	GO 12-SME/SP2	30.3 A	66 mV/A	12 A	5 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Ratio	Grade 1	
	GO 15-SME/SP4	37.5 A	33.333 mV/A	15 A	3.3 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Ratio	Grade 1	
	GO 20-SME	50 A	40 mV/A	20 A	5 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Fixed	Grade 1	
	GO 20-SME/SP2	50 A	40 mV/A	20 A	5 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Ratio	Grade 1	
	GO 20-SME/SP3	50 A	25 mV/A	20 A	3.3 V	SOIC 8	0 to 300 kHz	No	-40...125°C	Fixed	Grade 1	
GO SMS	GO 4-SMS/SP3	10.4 A	120 mV/A	4.17 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 8-SMS/SP4	20 A	62.5 mV/A	8 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Ratio	Grade 1	
	GO 10-SMS	25 A	80 mV/A	10 A	5 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 10-SMS/SP3	25 A	50 mV/A	10 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 12-SMS/SP4	30 A	41.67 mV/A	12 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Ratio	Grade 1	
	GO 20-SMS	50 A	40 mV/A	20 A	5 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 20-SMS/SP3	50 A	25 mV/A	20 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 30-SMS	75 A	26.667 mV/A	30 A	5 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 30-SMS/SP3	75 A	16.667 mV/A	30 A	3.3 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	GO 36-SMS	90 A	22.22 mV/A	36 A	5 V	SOIC 16	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
HMSR SMS	HMSR 6-SMS	15 A	133.333 mV/A	6 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 6-SMS/SP11	15 A	133.333 mV/A	6 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	HMSR 8-SMS	20 A	100 mV/A	8 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 8-SMS/SP11	20 A	100 mV/A	8 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	HMSR 10-SMS	25 A	80 mV/A	10 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 10-SMS/SP11	25 A	80 mV/A	10 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	HMSR 15-SMS	37.5 A	53.333 mV/A	15 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 15-SMS/SP11	37.5 A	53.333 mV/A	15 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	HMSR 20-SMS	50 A	40 mV/A	20 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 20-SMS/SP11	50 A	40 mV/A	20 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	
	HMSR 30-SMS	75 A	26.667 mV/A	30 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR 30-SMS/SP11	75 A	26.667 mV/A	30 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	Grade 1	

	Model	Measuring Range	Sensitivity	Nominal Current	Supply Voltage	Package	Bandwidth	Overcurrent Detection	Temperature Range	Output	AEC-Q Qualification	Visual Appearance
HMSR DA	HMSR DA 15-6-50000	15 A	2.666%/A ($\Sigma\Delta$ Output)	6 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR DA 15-6-54000	15 A	2.666%/A ($\Sigma\Delta$ Output)	6 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR DA 25-10-50000	25 A	1.6%/A ($\Sigma\Delta$ Output)	10 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR DA 25-10-54000	25 A	1.6%/A ($\Sigma\Delta$ Output)	10 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR DA 75-30-50000	75 A	0.533%/A ($\Sigma\Delta$ Output)	30 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
	HMSR DA 75-30-54000	75 A	0.533%/A ($\Sigma\Delta$ Output)	30 A	5 V	SOIC 10	0 to 300 kHz	Yes	-40...125°C	Fixed	No	
GXS AFE	GXS AFE 20-30010A	20 A	66 mV/A	8 A	3.3 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 20-50010A	29 A	100 mV/A	8 A	5 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 30-30110A	30 A	44 mV/A	12 A	3.3 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Ratio	No	
	GXS AFE 40-30010A	40 A	33 mV/A	16 A	3.3 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 50-50010A	50 A	40 mV/A	20 A	5 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 65-30010A	65 A	20.31 mV/A	26 A	3.3 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 65-50010A	65 A	30.77 mV/A	26 A	5 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Fixed	No	
	GXS AFE 66-31110A	66 A	40 mV/A	26 A	3.3 V	SOIC 8L	0 to 1000 kHz	Yes	-40...125°C	Ratio	No	
GXS ANF	GXS ANF 5-2 30001A	5 A	264 mV/A	2 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 5-2 50101A	5 A	400 mV/A	2 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 10-4 30001A	10 A	132 mV/A	4 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 10-4 30101A	10 A	132 mV/A	4 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 10-4 31101A	10 A	264 mV/A	4 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 10-4 50001A	10 A	200 mV/A	4 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 10-4 50101A	10 A	200 mV/A	4 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 10-4 51101A	10 A	400 mV/A	4 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 20-8 30001A	20 A	66 mV/A	8 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 20-8 30101A	20 A	66 mV/A	8 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 20-8 50001A	20 A	100 mV/A	8 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 20-8 50101A	20 A	100 mV/A	8 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 20-8 51101A	20 A	200 mV/A	8 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 25-10 50001A	25 A	80 mV/A	10 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	

	Model	Measuring Range	Sensitivity	Nominal Current	Supply Voltage	Package	Bandwidth	Overcurrent Detection	Temperature Range	Output	AEC-Q Qualification	Visual Appearance
GXS ANF	GXS ANF 25-10 50101A	25 A	80 mV/A	10 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 30-12 30001A	30 A	44 mV/A	12 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 30-12 30101A	30 A	44 mV/A	12 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 30-12 50001A	30 A	66.67 mV/A	12 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 30-12 50101A	30 A	66.67 mV/A	12 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 30-12 51101A	30 A	133.3 mV/A	12 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 40-16 30101A	40 A	33 mV/A	16 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 40-16 50101A	40 A	50 mV/A	16 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 50-20 30101A	50 A	26.4 mV/A	20 A	3.3 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 50-20 50001A	50 A	40 mV/A	20 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Fixed	No	
	GXS ANF 50-20 50101A	50 A	40 mV/A	20 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
	GXS ANF 50-20 51001A	50 A	80 mV/A	20 A	5 V	SOIC 8L	0 to 400 kHz	No	-40...125°C	Ratio	No	
GXN AFE	GXN AFE 50-50010A	50 A	40 mV/A	20 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 65-50010A	65 A	30.77 mV/A	26 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 66-30010A	66 A	20 mV/A	26 A	3.3 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 80-50010A	80 A	30.77 mV/A	32 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 100-30010A	100 A	13.2 mV/A	40 A	3.3 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 100-50010A	100 A	20 mV/A	40 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	No	
	GXN AFE 40-50010Q	40 A	50 mV/A	16 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	Grade 0	
	GXN AFE 50-50010Q	50 A	40 mV/A	20 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	Grade 0	
	GXN AFE 65-50010Q	65 A	30.8 mV/A	26 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	Grade 0	
	GXN AFE 66-30010Q	66 A	20 mV/A	26 A	3.3 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	Grade 0	
	GXN AFE 100-50010Q	100 A	20 mV/A	40 A	5 V	SOIC 16L	0 to 1000 kHz	Yes	-40...150°C	Fixed	Grade 0	
GXN ANC	GXN ANC 10-4 30011A	10 A	132 mV/A	4 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 20-8 30011A	20 A	66 mV/A	8 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 20-8 50011A	20 A	100 mV/A	8 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 25-10 30011A	25 A	52.8 mV/A	10 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 30-12 31011A	30 A	88 mV/A	12 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 30-12 50011A	30 A	66.67 mV/A	12 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	

	Model	Measuring Range	Sensitivity	Nominal Current	Supply Voltage	Package	Bandwidth	Overcurrent Detection	Temperature Range	Output	AEC-Q Qualification	Visual Appearance
GXN ANC	GXN ANC 33-13 30011A	33 A	39.6 mV/A	13 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 40-16 50011A	40 A	50 mV/A	16 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 50-20 50011A	50 A	40 mV/A	20 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 66-26 30011A	66 A	20 mV/A	26 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 66-26 50011A	66 A	30.3 mV/A	26 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 80-32 30011A	80 A	16.5 mV/A	32 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 80-32 50011A	80 A	25 mV/A	32 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN ANC 100-40 30011A	100 A	13.2 mV/A	40 A	3.3 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
GXN AND	GXN ANC 100-40 50011A	100 A	20 mV/A	40 A	5 V	SOIC 16L	0 to 320 kHz	Yes	-40...125°C	Fixed	No	
	GXN AND 20-8 30111A	20 A	66 mV/A	8 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 20-8 50011A	20 A	100 mV/A	8 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 20-8 50111A	20 A	100 mV/A	8 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 25-10 30011A	25 A	52.8 mV/A	10 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 30-12 30011A	30 A	44 mV/A	12 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 30-12 30111A	30 A	44 mV/A	12 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 30-12 50011A	30 A	66.67 mV/A	12 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 30-12 50111A	30 A	66.67 mV/A	12 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 30-12 51111A	30 A	133.33 mV/A	12 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 40-16 30111A	40 A	33 mV/A	16 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 40-16 50011A	40 A	50 mV/A	16 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 50-20 50011A	50 A	40 mV/A	20 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 50-20 50111A	50 A	40 mV/A	20 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 50-20 51111A	50 A	80 mV/A	20 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 66-26 30011A	66 A	20.3 mV/A	26 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 66-26 30111A	66 A	20.3 mV/A	26 A	3.3 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 66-26 50011A	66 A	30.77 mV/A	26 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 66-26 50111A	66 A	30.77 mV/A	26 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	
	GXN AND 80-32 50011A	80 A	25 mV/A	32 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 100-40 50011A	100 A	20 mV/A	40 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Fixed	No	
	GXN AND 100-40 50111A	100 A	20 mV/A	40 A	5 V	SOIC 16L	0 to 240 kHz	No	-40...125°C	Ratio	No	

	Model	Measuring Range	Sensitivity	Nominal Current	Supply Voltage	Package	Bandwidth	Overcurrent Detection	Temperature Range	Output	AEC-Q Qualification	Visual Appearance
GXM AFE	GXM AFE 50-50010A	50 A	40 mV/A	20 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 50-51010A	50 A	80 mV/A	20 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 65-50010A	65 A	30.77 mV/A	26 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 100-30010A	100 A	13.2 mV/A	40 A	3.3 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 100-51010A	100 A	40.2 mV/A	40 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 150-50010A	150 A	13.33 mV/A	60 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	No	
	GXM AFE 66-30010Q	66 A	20 mV/A	26 A	3.3 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	Grade O	
	GXM AFE 100-30010Q	100 A	13.2 mV/A	40 A	3.3 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	Grade O	
	GXM AFE 100-50010Q	100 A	20 mV/A	40 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	Grade O	
	GXM AFE 180-50010Q	180 A	11.1 mV/A	72 A	5 V	SOIC 10L	0 to 1000 kHz	Yes	-40...150°C	Ratio	Grade O	
GXM ANC	GXM ANC 50-20 30010A	50 A	26.4 mV/A	20 A	3.3 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 50-20 50010A	50 A	40 mV/A	20 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 75-30 30010A	75 A	17.6 mV/A	30 A	3.3 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 75-30 50030A	75 A	26.67 mV/A	30 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 80-32 30010A	80 A	16.5 mV/A	32 A	3.3 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 80-32 50010A	80 A	25 mV/A	32 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 100-40 30010A	100 A	13.2 mV/A	40 A	3.3 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 100-40 50010A	100 A	20 mV/A	40 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 100-40 50030A	100 A	20 mV/A	40 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 100-40 51030A	100 A	41.2 mV/A	40 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 110-44 30010A	110 A	12 mV/A	44 A	3.3 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 150-60 50010A	150 A	13.3 mV/A	60 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 150-60 50030A	150 A	13.3 mV/A	60 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 150-60 51030A	150 A	27.47 mV/A	60 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 200-80 50010A	200 A	10 mV/A	80 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	
	GXM ANC 200-80 50020A	200 A	10 mV/A	80 A	5 V	SOIC 10L	0 to 320 kHz	Yes	-40...150°C	Ratio	No	